

# Instruction Sheet - Display Racks

## Model LD4 and LD5

Congratulations for having chosen an excellent Luxor product.

Your purchase is backed by Luxor's satisfaction guarantee. Luxor is a service oriented company. As a service to you, we are enclosing a "satisfaction guaranteed" request card. Should a problem arise needing our assistance simply fill out the card and fax it to us toll-free or mail postage paid to Luxor. Be sure to include your telephone number. Upon receipt of your service request, we will give it immediate attention to be sure that you will be completely satisfied with your purchase. Thank you for your confidence.



Customer Service Department  
LUXOR  
2245 Delany Road  
Waukegan, IL 60087



Ed

### Parts List

- |                                   |                                 |
|-----------------------------------|---------------------------------|
| 1 - Round Bar w/End Caps and Nuts | 2 - Rear Upright Tubes          |
| 1 - Left Caster Tube              | 2 - Casters                     |
| 1 - Right Caster Tube             | 2 - Caster With Brake           |
| 1 - Slotted Tube                  | 2 - Plastic Round Handles       |
| 1 - Lower Back Tube               | 10 - Screws                     |
| 1 - Upper Back Tube               | LD4 - 8 Pockets/ 1 Face Plate   |
| 2 - Front Upright Tubes           | LD5 - 16 Pockets/ 2 Face Plates |

Tools Required: 9/16 wrench - Phillips Screwdriver

### ASSEMBLY

- Separate and identify all parts. Model LD4 and 5 assemble the same way and parts are numbered the same. The LD5 is pictured in the diagram only for reference during assembly. Match numbers on tubes for proper assembly. Numbers are stamped into each tube on the ends of tube.
- Take left caster tube (#1 and #2) and left front tube #2 and carefully insert left front tube into tube connector on the end that has a #2 stamped on it. Make sure all hole locations are like those in the diagram. Secure with screw and phillips screwdriver.
- Next, match left caster tube #1 with left rear tube. (#1 and #5) make sure tube is facing the same way as the diagram then secure with screw.
- Insert round plastic handle into ends of each tube as shown.
- Next, take the right caster tube and as in the previous steps match tubes using the numbers stamped in each tube always watching your hole locations and direction the tube is facing. Secure using screws provided. Insert round plastic handle into ends of each tube as shown.
- Take left side (#2 is the front and #1 is the back) and insert round threaded bar through hole and secure using end cap. Take slotted bar (#2 and #4) and match numbers make sure slot is facing up and secure using screw. Take back bottom bar and match numbers on tube and secure using screws. Follow the same procedure for upper back tube be sure numbers and hole locations are correct then secure using screws.
- Attach right side to left side assembly using screws. Recheck to make sure all tubes are in the correct position and all numbers match.
- Screw casters into caster sockets on the bottom of assembled stand. The casters with brake go in front. A 9/16 wrench may be needed to fully seat casters.
- To assemble plastic pockets locate the four snap plugs on the back of each part and insert into the four holes on the front of each part. Then pull on one and push down on the other until the two parts "snap" together. Follow the same procedure to snap on the face plate. Then set the pockets inside the stand and let two snap plugs set over metal braces on back tube and front of pockets to set down into slot on slotted tube.
- Always move display racks slowly. Put in desired position and lock into place using casters with brake. Only adults should move display racks. Assembly is complete.

\* Be sure parts are fully joined together. parts "snap" together

